



## PST02-C 3 in 1 Multi Sensor

- Farer Range, Faster, Smarter, Thin, Small and Multi functions
- Fitting your home decoration style
- Extremely low power consumption
- Easy and quick to install
- Z-wave wireless systems integration
- Door/Windows , Illumination , Temperature 4 in 1 Sensor



|                       |   |
|-----------------------|---|
| Supply Voltage        | 3.0 V by CR123A/1700mAh   |
| RF distance           | Min. 30M indoor,<br>100M outdoor line of sight,   |
| RF Frequency          | 908.4MHz,916MHz (U.S. A./Mexico)<br>868.4MH, 869.85MHz ( EU)<br>922.5MHz, 923.9MHz, 926.3MHz (JP) Transceiver |
| Chip                  | Z-wave 500 Series Module  |
| Battery Life          | CR123A 2~7 years (Depend trigger time interval)   |
| Sensitivity           |   |
| Magnetic Gap          | 30 mm   |
| Illumination          | 0 ~ 500 Lux   |
| Measurement           |   |
| Temperature           | -10~40 °C ±1.5 °C   |
| Illumination          | Detector 20 lux max. (Level 1) 90 lux typ. (Level 90)   |
| Dimension             | Detector 96(L) x 28(W) x 23(H) mm<br>Magnet 50(L) x 12(W) x 10(H) mm  |
| Weight                | Detector 40 g / Magnet 9.2 g  |
| IP classification     | indoor use  |
| Operation Temperature | -10 ~ 40°C  |
| Operation Humidity    | 85%RH max   |



### PHILIO TECHNOLOGY CORPORATION

8F., No. 653-2, Zhongzheng Rd., Xinzhuang Dist., New Taipei City 24257, Taiwan  
 sales@philio-tech.com Tel:+886-2-2908-8952 Fax:+886-2-29088652