



86-101

86-101
IOT Z-Wave Plug-in dimmer module; White

Features

- Works with incandescent and most dimmable fluorescent (CFL), or LED lighting
- LED backlit Key for manual ON/OFF and status indicator
- Z-Wave Plus Certified
- Powered by Sigma Design 500 Series module inside
- Functions as a Z-Wave signal repeater



86-101

Specification Notes: GROUP/ALL enabled, if supported by controller; Multiple scene control using double and triple tap; Supports Central Scene command class; Over-The-Air firmware upgrade available, if supported by controller; Supports Network Wide Inclusion (inclusion through a repeater), if supported by controller.

Needs a Z-Wave compatible controller

| Item Number | UPC | Finish | Height | Width | Length | Pack | UL Classification |
|-------------|--------------|--------|--------|--------|--------|------|-------------------|
| 86-101 | 045923861017 | White | 1-1/2" | 2-1/8" | 3-1/4" | 40 | cULus - Listed |



National Toll-Free:
800.43.SATCO
(800.437.2826)
www.satco.com

Distribution Centers:
New York, Florida, Texas,
Washington, California,
Puerto Rico

Corporate Offices:
110 Heartland Blvd.,
Brentwood, NY 11717
800.437.2826 631.243.2022
Fax 631.243.2027

